

GRAPHIC WRITER COMMAND CONTROL KEYS

CTRL	FUNCTION	DEFAULT
A	Ask For Help. Shows help screen.	
B	Background Color. + 2 digit number (00 to 31)	00 (black)
C	Caps Lock. Selects lowercase or uppercase.	Uppercase
D	Default Window. Resets window to full screen.	
E	Erase Window. Erases to background color.	
F	Foreground Color. + 2 digit number (00 to 31)	31 (white)
G	Graphic Input. Selects current graphic input device.	Off
H	Backspace. Same as left arrow on keyboard.	
I	Inverse. Print as negative image (cancels N)	Off
J	Linefeed. Same as down arrow on keyboard.	
K	Reverse Linefeed. Same as up arrow on keyboard.	
L	Linefeed Spacing. + 2 digit number (00 to 99)	02
M	Carriage Return. Same as RETURN on keyboard.	
N	Normal. Print as positive image (cancels I)	On
O	Overlay. Overlay background (cancels R and T)	Off
P	Point Mode. Draw with single dot. RETURN or Graphic Input drops dot. (non-ctrl key to cancel)	Off
Q	Quit. Quits to Graphic Writer Menu.	
R	Replace. Replace background (cancels O and T)	On
S	Spacing between characters. + 2 digit number. (00 to 99)	01
T	Transparent. Invert background. (cancels R and O)	Off
U	Forward space. Same as forward arrow on keyboard.	
V	Viewport. View file parameters (again to close)	Closed
W	Window. Set window. I,J,K,M, Arrows to move the Corner markers. RETURN to accept placement.	Full Screen
X	Backslash Character.	
Y	Yank Screen From Disk (Graffile only)	
Z	Zero Cursor. Place Cursor in upper-left of screen.	
ESC	Escape Mode. Use I,J,K,M, and Arrows to move the cursor one dot at a time. (Any key except I,J,K,M, and Arrow keys to cancel)	Off

FONTRIX FONT EDITOR

SET PARAMETERS	LIMITS	COMMENTS
Set Name	1 to 15 characters	Alphanumerics and period only
Total Characters	1 to 94	
First Character	"!"=first, "~"=last	
Horizontal Cell Size	1 to 32	
Vertical Cell Size	1 to 32	
Proportional	yes or no	

EDIT SET COMMAND KEYS

KEY	FUNCTION
I,J,K,M, and Arrows	Move cursor to choose which character to edit.
V	View the entire set (again to cancel)
C	Copy one character cell into another.
O	Overlay one character cell over another.
RETURN	Select a character for editing.
Q	Quit and return to Font Editor Menu.

EDIT SINGLE CHARACTER COMMAND KEYS

KEY	FUNCTION
I,J,K,M, and Arrows	Move cursor within character cell.
Space Bar	Change a pixel. (If was Off turn On. If was On turn Off)
CTRL-E	Erase contents of character cell.
CTRL-P	Position within cell. (I,J,K,M,Arrows) (any other to cancel)
CTRL-X	Return to Edit Set without saving changes to character.
RETURN	Return to Edit Set and save changes to character.